

Sigtronics UltraSound
 12 Way Intercom
 2 Radios
 4 Transmit Positions

Model: **US-12D**
US-DRE

Connectors Grouped By Pinout

J1 Connector P/N 800187 — Headset Jack and PTT Switch		
Pin	Color	Function
1	White / Black	Officer Mic
2	White / Red	Officer PTT
3	Blue	Headphones
4	Black	Headset & PTT Return
5	Orange	Crew 4 Mic
6	White / Green	Crew 4 PTT
7	Red	+12 Volts DC
8	White / Brown	Crew 3 Mic
9	Yellow	Crew 3 PTT
10	White / Blue	Driver PTT
11	White / Orange	Driver Mic
12	Green	Power Ground

J4 Connector P/N 800189 — Headset Jack		
Pin	Color	Function
1	Tan	Crew 5 Mic
2	Tan	Crew 6 Mic
3	Tan	Crew 7 Mic
4	Tan	Crew 8 Mic
5	Tan	Crew 9 Mic
6	Tan	Crew 10 Mic
7	Tan	Crew 11 Mic
8	Tan	Crew 12 Mic
9	Black	Headset & PTT Return

J2 Connector P/N 800098 — Radio 1		
Pin	Color	Function
1	Brown	Mic Hi
2	Violet	Speaker Hi
3	Violet	Speaker Low
4	Black	Mic Low
5	White	PTT Hi
6	White	PTT Low

J3 Connector P/N 800098 — Radio 2		
Pin	Color	Function
1	Brown	Mic Hi
2	Violet	Speaker Hi
3	Violet	Speaker Low
4	Black	Mic Low
5	White	PTT Hi
6	White	PTT Low

Jack Wiring	
Headphone	Tip
Microphone	Ring
Common Return	Barrel

Sigtronics Corporation

178 East Arrow Highway
 San Dimas, CA 91773
 Phone: (909) 305-9399

E-mail: info@sigtronics.com
 Web Site: www.sigtronics.com



Sigtronics UltraSound
 12 Way Intercom
 2 Radios
 4 Transmit Positions

Model: **US-12D**
US-DRE

Connectors Grouped By Function

J1 Connector P/N 800187 — Headset Jack and PTT Switch		
Pin	Color	Function
1	White / Black	Officer Mic
2	White / Red	Officer PTT
11	White / Orange	Driver Mic
10	White / Blue	Driver PTT
8	White / Brown	Crew 3 Mic
9	Yellow	Crew 3 PTT
5	Orange	Crew 4 Mic
6	White / Green	Crew 4 PTT
3	Blue	Headphones
4	Black	Headset & PTT Return
7	Red	+12 Volts DC
12	Green	Power Ground

J4 Connector P/N 800189 — Headset Jack		
Pin	Color	Function
1	Tan	Crew 5 Mic
2	Tan	Crew 6 Mic
3	Tan	Crew 7 Mic
4	Tan	Crew 8 Mic
5	Tan	Crew 9 Mic
6	Tan	Crew 10 Mic
7	Tan	Crew 11 Mic
8	Tan	Crew 12 Mic
9	Black	Headset & PTT Return

J2 Connector P/N 800098 — Radio 1		
Pin	Color	Function
1	Brown	Mic Hi
4	Black	Mic Low
2	Violet	Speaker Hi
3	Violet	Speaker Low
5	White	PTT Hi
6	White	PTT Low

J3 Connector P/N 800098 — Radio 2		
Pin	Color	Function
1	Brown	Mic Hi
4	Black	Mic Low
2	Violet	Speaker Hi
3	Violet	Speaker Low
5	White	PTT Hi
6	White	PTT Low

Jack Wiring	
Headphone	Tip
Microphone	Ring
Common Return	Barrel

Sigtronics Corporation

178 East Arrow Highway San Dimas, CA 91773
 Phone: (909) 305-9399

E-mail: info@sigtronics.com
 Web Site: www.sigtronics.com



